



# EPCOM syscom

1630 Paisano Dr. El Paso. Tx 79901. Ph (915)533-5119 [www.epcom.net](http://www.epcom.net)

## SYSCOM

Ave 20 de Noviembre No. 805 Col. Centro Chihuahua, Chih. 31000

Tel 052 (614) 415 – 2525 [www.syscom.mx](http://www.syscom.mx)

# TK-7302/7302(V)/7302H/7302H(V)

## PARTS LIST

\* New Parts. Δ indicates safety critical components.

Parts without **Parts No.** are not supplied.

Les articles non mentionnes dans le **Parts No.** ne sont pas fournis.

Teile ohne **Parts No.** werden nicht geliefert.

L : Scandinavia

Y : PX (Far East, Hawaii)

C : China

K : USA

T : England

X : Australia

P : Canada

E : Europe

M : Other Areas

TK-7302/7302(V)/7302H/7302H(V)

DISPLAY UNIT (X54-3670-20), TX-RX UNIT (X57-7680-XX)

Ref. No.	Address	New parts	Parts No.	Description	Desti-nation	Ref. No.	Address	New parts	Parts No.	Description	Desti-nation
<b>TK-7302/7302(V)/7302H/7302H(V)</b>						CN1		*	E40-6851-05	FLAT CABLE CONNECTOR	
1	1B	*	A02-4073-11	PLASTIC CABINET		CN2			E23-1262-05	TERMINAL	
2	3A	*	A62-1171-03	PANEL ASSY		J1	3A	*	E58-0535-05	MODULAR JACK	
4	2B	*	B09-0732-03	CAP (D-SUB)		101	3A	*	J31-0565-15	COLLAR	
5	3A	*	B10-2794-03	FRONT GLASS		L1			L92-0138-05	CHIP FERRITE	
6	3A	*	B43-1629-04	BADGE		CP1			RK74HB1J102J	CHIP-COM 1.0K J 1/16W	
7	2D	*	B62-2150-10	INSTRUCTION MANUAL	M,HM	R1			RK73HB1J101J	CHIP R 100 J 1/16W	
7	2D	*	B62-2167-10	INSTRUCTION MANUAL	K,HK,HVK	R2			RK73FB2B100J	CHIP R 10 J 1/8W	
9	2B		E04-0167-15	RF COAXIAL RECEPTACLE (M)		R3-8			RK73HB1J102J	CHIP R 1.0K J 1/16W	
10	1C		E30-7523-55	DC CORD ASSY ACCESSORY		R10,11			RK73HB1J102J	CHIP R 1.0K J 1/16W	
11	2B	*	E30-7684-05	DC CORD		R12			RK73HB1J122J	CHIP R 1.2K J 1/16W	
12	2A	*	E37-1461-05	FLAT CABLE (30P PANEL)		R21			RK73HB1J222J	CHIP R 2.2K J 1/16W	
14	1C		F52-0023-05	FUSE (BLADE TYPE) 10A ACCESSORY	M,K	R22			RK73HB1J820J	CHIP R 82 J 1/16W	
14	1C		F52-0024-05	FUSE (BLADE TYPE) 15A ACCESSORY	HM,HK,HVK	R23			RK73HB1J121J	CHIP R 120 J 1/16W	
16	2B		G53-1643-04	PACKING (DC CORD)		R26,27			RK73HB1J000J	CHIP R 0.0 J 1/16W	
17	2B		G53-1662-04	PACKING (RECEPTACLE)		R28,29			RK73HB1J103J	CHIP R 10K J 1/16W	
18	1B	*	G53-1819-21	PACKING (CHASSIS)		R34			RK73HB1J102J	CHIP R 1.0K J 1/16W	
19	3A	*	G53-1820-03	PACKING (PANEL)		R35			RK73HB1J223J	CHIP R 22K J 1/16W	
21	1C,1D		H12-3178-05	PACKING FIXTURE		R36			RK73HB1J822J	CHIP R 8.2K J 1/16W	
22	2D	*	H52-2310-12	ITEM CARTON CASE		R37,38			RK73HB1J100J	CHIP R 10 J 1/16W	
24	3D		J19-1584-15	HOLDER (MIC HANGER)	K,HK,HVK	R39			RK73HB1J150J	CHIP R 15 J 1/16W	
25	3B	*	J19-5528-03	HOLDER (SPEAKER)		R40			RK73HB1J100J	CHIP R 10 J 1/16W	
26	1C		J29-0726-03	BRACKET ACCESSORY		R41			RK73HB1J222J	CHIP R 2.2K J 1/16W	
28	3A	*	K29-9448-01	KEY TOP		R42			RK73HB1J102J	CHIP R 1.0K J 1/16W	
A	1A,1B		N35-2604-43	BINDING HEAD MACHINE SCREW		D20			DA221	DIODE	
B	1A,2A,2B		N67-3008-48	PAN HEAD SEMS SCREW		D33			O2D26.2F-Y	ZENER DIODE	
C	3A,3B		N80-2008-48	PAN HEAD TAPTITE SCREW		D37	3A	*	HDSP-521A	LED	
D	2A,2B		N87-2608-48	BRAZIER HEAD TAPTITE SCREW		IC1		*	TCA62746AFNAG	MOS-IC	
30	3D		N99-2039-05	SCREW SET ACCESSORY		Q1,2			RT1N441U	TRANSISTOR	
32	3A	*	T07-0785-05	SPEAKER		Q3			KRA225S	DIGITAL TRANSISTOR	
33	2C	*	T91-0624-65	MICROPHONE (KMC-30) ACCESSORY	HK	Q4			KRC102S-P	DIGITAL TRANSISTOR	
34	2C	*	T91-0639-55	MICROPHONE (KMC-35) ACCESSORY	K,HVK	O5,6			2SC3928A	TRANSISTOR	
						Q7,8			RT1P141U	TRANSISTOR	
						Q9			2SC3928A	TRANSISTOR	

# TK-7302/7302(V)/7302H/7302H(V)

## EXPLODED VIEW

