

Model	Freq. Range (MHz)	FWD Power	RFL Power	FWD Element	RFL Element
DPM-50H	Feb-30	1.25 W to 50 W	125 mW to 5 W	DPM-50H	DPM-5H
DPM-500H	Feb-30	12.5 W to 500 W	1.25 W to 50 W	DPM-500H	DPM-50H
DPM-50A	25-60	1.25 W to 50 W	125 mW to 5 W	DPM-50A	DPM-5A
DPM-500A	25-60	12.5 W to 500 W	1.25 W to 50 W	DPM-500A	DPM-50A
DPM50B	50-125	1.25 W to 50 W	125 mW to 5 W	DPM-50B	DPM-5B
DPM-500B	50-125	12.5 W to 500 W	1.25 W to 50 W	DPM-500B	DPM-50B
DPM-1000B	50-125	25 W to 1.0 kW	2.5 W to 100 W	DPM-1000B	DPM-100B
DPM-50C	100-250	1.25 W to 50 W	125 mW to 5 W	DPM-50C	DPM-5C
DPM-500C	100-250	12.5 W to 500 W	1.25 W to 50 W	DPM-500C	DPM-50C
DPM-2500C	100-250	62.5 W to 2.5 kW	6.25 W to 250 W	DPM-2500C	DPM-250C
DPM-5D	200-500	125 mW to 5 W	12.5 mW to 500 mW	DPM-5D	DPM-.5D
DPM-50D	200-500	1.25 W to 50 W	125 mW to 5 W	DPM-50D	DPM-5D
DPM-500D	200-500	12.5 W to 500 W	1.25 W to 50 W	DPM-500D	DPM-50D
DPM-5E-400	400-800	125 mW to 5 W	12.5 mW to 500 mW	DPM-5E-400	DPM-.5E-400
DPM-50E-400	400-800	1.25 W to 50 W	125 mW to 5 W	DPM-50E-400	DPM-5E-400
DPM-100E-400	400-800	2.5 W to 100 W	250 mW to 10 W	DPM-100E-400	DPM-10E-400
DPM-500E-400	400-800	12.5 W to 500 W	1.25 W to 50 W	DPM-500E-400	DPM-50E-400
DPM-1000E-400	400-800	25 W to 1.0 kW	2.5 W to 100 W	DPM-1000E-400	DPM-100E-400
DPM-5E-800	800-960	125 mW to 5 W	12.5 mW to 500 mW	DPM-5E-800	DPM-.5E-800
DPM-50E-800	800-960	1.25 W to 50 W	125 mW to 5 W	DPM-50E-800	DPM-5E-800
DPM-100E-800	800-960	2.5 W to 100 W	250 mW to 10 W	DPM-100E-800	DPM-10E-800
DPM-500E-800	800-960	12.5 W to 500 W	1.25 W to 50 W	DPM-500E-800	DPM-50E-800
DPM-1000E-800	800-960	25 W to 1.0 kW	2.5 W to 100 W	DPM-1000E-800	DPM-100E-800