



## Specifications

**Normal operating voltage:** 15 to 32 VDC.

**Maximum current draw:** 7.5 mA (LED on).

**Average operating current:** 7.5 mA group poll (FlashScan® mode) with LED flashing.

**External supply voltage** (*between Terminals T3 and T4*): maximum 28 VDC.

**EOL resistance:** 3.9K ohms.

**Temperature range:** 32°F to 120°F (0°C to 49°C).

**Humidity range:** 10% to 93% non-condensing.

**Dimensions:** 4.5" (11.43 cm) high x 4" (10.16 cm) wide x 1.25" (3.175 cm) deep. Mounts to a 4" (10.16 cm) square x 2.125" (5.398 cm) deep box.

**Weight:** 6.3 oz.

### SOFTWARE COMPATIBILITY

- NFS-640 - As of Version 3.1.3
- NFS-3030 - As of Version 2.2.9
- LCM - As of Version 2.3.7

## Product Line Information

**FTM-1:** Intelligent Addressable Firephone Control Module, 3.9K ohm End-of-Line Resistor included.

**FTM-1A:** Same as FTM-1 with ULC listing.

**SMB500:** Optional Surface-Mount Electrical Backbox.

**CB500:** Control Module Barrier — required by UL for separating power-limited and non-power-limited wiring in the same junction box as FTM-1.

---

Notifier® and FlashScan® are registered trademarks of Honeywell International Inc. Microsoft® and Windows® are registered trademarks of Microsoft Corporation.

©2010 by Honeywell International Inc. All rights reserved. Unauthorized use of this document is strictly prohibited.



This document is not intended to be used for installation purposes.  
We try to keep our product information up-to-date and accurate.  
We cannot cover all specific applications or anticipate all requirements.  
All specifications are subject to change without notice.



Made in the U.S. A.

For more information, contact Notifier. Phone: (203) 484-7161, FAX: (203) 484-7118.  
[www.notifier.com](http://www.notifier.com)