

TK-2302/2302(V)/2306

PARTS LIST

TX-RX UNIT (X57-7570-20)

Ref. No.	Address	New parts	Parts No.	Description	Desti-nation	Ref. No.	Address	New parts	Parts No.	Description	Desti-nation
R309,310			RK73GB2A000J	CHIP R 0.0 J 1/10W		S1-3			S70-0414-05	TACT SWITCH	
R313			RK73HB1J102J	CHIP R 1.0K J 1/16W		MIC301	2A		T91-0651-15	MIC ELEMENT (ECM)	
R314,315			RK73HB1J103J	CHIP R 10K J 1/16W		D3,4			1SV325F	VARIABLE CAPACITANCE DIODE	
R316			RK73HB1J222J	CHIP R 2.2K J 1/16W		D6			1SV325F	VARIABLE CAPACITANCE DIODE	
R317			RK73HB1J472J	CHIP R 4.7K J 1/16W		D8			1SV325F	VARIABLE CAPACITANCE DIODE	
R318			RK73HB1J182J	CHIP R 1.8K J 1/16W		D9			1SV278F	VARIABLE CAPACITANCE DIODE	
R319			RK73HB1J000J	CHIP R 0.0 J 1/16W		D10			MC2858	DIODE	
R320			RK73HB1J123J	CHIP R 12K J 1/16W		D101			UDZW5.1(B)	ZENER DIODE	
R321			RK73HB1J103J	CHIP R 10K J 1/16W		D103			HSC277	DIODE	
R323			RK73HB1J102J	CHIP R 1.0K J 1/16W		D104,105			HVC131	DIODE	
R324,325			RK73HB1J472J	CHIP R 4.7K J 1/16W		D202-205			1SV305F	VARIABLE CAPACITANCE DIODE	
R340-342			RK73HB1J103J	CHIP R 10K J 1/16W		D301			GN1G	DIODE	
R344			RK73HB1J474J	CHIP R 470K J 1/16W		D302		*	HRC0203C	DIODE	
R345			RK73HB1J273J	CHIP R 27K J 1/16W		D306		*	KDR731	DIODE	
R347			RK73GB2A000J	CHIP R 0.0 J 1/10W		D307		*	MC2850	DIODE	
R348			RK73HB1J102J	CHIP R 1.0K J 1/16W		D308,309		*	KDR731	DIODE	
R349			RK73HB1J105J	CHIP R 1.0M J 1/16W		IC1			MB15A02PFV2E1	MOS-IC	
R350			RK73HB1J124J	CHIP R 120K J 1/16W		IC2			UPB1509GV	BI-POLAR IC	
R351			RK73HB1J334J	CHIP R 330K J 1/16W		IC101		*	BA2904FVM	MOS-IC	
R352			RK73HB1J104J	CHIP R 100K J 1/16W		IC201			TA31136FNG	MOS-IC	
R353			RK73HB1J123J	CHIP R 12K J 1/16W		IC301			BD4840FVE	MOS-IC	
R354			RK73HB1J334J	CHIP R 330K J 1/16W		IC303			XC6209B502PR	MOS-IC	
R355			RK73HB1J124J	CHIP R 120K J 1/16W		IC304		*	XC6209B502MR	MOS-IC	
R356			RK73HB1J472J	CHIP R 4.7K J 1/16W		IC305		*	BR24L16F-W	ROM IC	
R357			RK73HB1J563J	CHIP R 56K J 1/16W		IC306		*	RSF212CCKCMB	MICRO CONTROL UNIT	
R358			RK73HB1J474J	CHIP R 470K J 1/16W		IC308			AQUA-L	MOS-IC	
R359			RK73HB1J473J	CHIP R 47K J 1/16W		IC309			TA7368FG	MOS-IC	
R360			RK73HB1J332J	CHIP R 3.3K J 1/16W		Q1		*	KTC4075E(Y,GR)	TRANSISTOR	
R361			RK73GB2A000J	CHIP R 0.0 J 1/10W		Q2		*	2SC4774	TRANSISTOR	
R362			RK73HB1J184J	CHIP R 180K J 1/16W		Q3			2SC5636	TRANSISTOR	
R363,364			RK73HB1J104J	CHIP R 100K J 1/16W		Q4,5			2SK1875-F(V)	FET	
R365			RK73HB1J332J	CHIP R 3.3K J 1/16W		Q6		*	KTC4075E(Y,GR)	TRANSISTOR	
R366			RK73HB1J154J	CHIP R 150K J 1/16W		Q7,8			RT1P430U	TRANSISTOR	
R367			RK73HB1J393J	CHIP R 39K J 1/16W		Q9			2SC5636	TRANSISTOR	
R368			RK73GB2A000J	CHIP R 0.0 J 1/10W		Q10		*	KTC4075E(Y,GR)	TRANSISTOR	
R369			RK73HB1J823J	CHIP R 82K J 1/16W		Q11			2SC5636	TRANSISTOR	
R370			RK73HB1J102J	CHIP R 1.0K J 1/16W		Q101			2SC4926YD	TRANSISTOR	
R371			RK73HB1J272J	CHIP R 2.7K J 1/16W		Q102			RQA0004PX0QS	FET	
R372			RK73HB1J000J	CHIP R 0.0 J 1/16W		Q103			RT1N441U	TRANSISTOR	
R373			RK73HB1J224J	CHIP R 220K J 1/16W		Q105			RD07MVS1BT122	FET	
R374			RK73HB1J123J	CHIP R 12K J 1/16W		Q106			RT1N441U	TRANSISTOR	
R375			RK73HB1J182J	CHIP R 1.8K J 1/16W		Q107			2SK1824-A	FET	
R376			RK73HB1J471J	CHIP R 470 J 1/16W		Q108			RT1P441U	TRANSISTOR	
R377			RK73HB1J473J	CHIP R 47K J 1/16W		Q201			RT1P441U	TRANSISTOR	
R378			RK73HB1J561J	CHIP R 560 J 1/16W		Q202		*	2SC4774	TRANSISTOR	
R379			RK73HB1J102J	CHIP R 1.0K J 1/16W		Q203,204			3SK318	FET	
R380			RK73HB1J474J	CHIP R 470K J 1/16W		Q301,302			RT1N441U	TRANSISTOR	
R381			RK73HB1J151J	CHIP R 150 J 1/16W		Q303			RT1P141U	TRANSISTOR	
R383			RK73HB1J563J	CHIP R 56K J 1/16W		Q304		*	DTB723YE	DIGITAL TRANSISTOR	
R384			RK73HB1J333J	CHIP R 33K J 1/16W		Q305,306			2SC4919	TRANSISTOR	
R385			RK73GB2A101J	CHIP R 100 J 1/10W		Q307			RT1N441U	TRANSISTOR	
R387			RK73HB1J104J	CHIP R 100K J 1/16W		Q308		*	KTC4075E(Y,GR)	TRANSISTOR	
R388			RK73HB1J101J	CHIP R 100 J 1/16W		Q310			2SC4116(GR)F	TRANSISTOR	
R389			RK73HB1J000J	CHIP R 0.0 J 1/16W		Q311			2SA1586(Y,GR)F	TRANSISTOR	
R390			RK73GB2A000J	CHIP R 0.0 J 1/10W		Q312			RT1N441U	TRANSISTOR	
R391			RK73HB1J102J	CHIP R 1.0K J 1/16W		Q313		*	2SB1694	TRANSISTOR	
R393			RK73GB2A000J	CHIP R 0.0 J 1/10W		Q314			RT1N441U	TRANSISTOR	
R394			RK73HB1J473J	CHIP R 47K J 1/16W		Q315,316			2SK3577-A	FET	
R398			RK73HB1J000J	CHIP R 0.0 J 1/16W							
VR1		*	R32-0737-05	SEMI FIXED VARIABLE RESISTOR							

